

TURNING AREAS ON / OFF BY THE KEYPAD

- ENTER YOUR PERSONALISED (**4 DIGIT CODE**), THEN PRESS THE **OK** KEY.



- IF THERE HAS BEEN AN ACTIVATION, AN ALARM MESSAGE WILL SCROLL ACROSS THE SCREEN. TO ACKNOWLEDGE AND CLEAR THIS MESSAGE, PRESS THE **OK** KEY.
- TO SELECT THE **AREA** YOU WISH TO TURN **ON** OR **OFF**, PRESS THE (^) OR (v) TO SCROLL THROUGH THE AREAS AVAILABLE.
- PRESS THE **ON** OR **OFF** KEYS TO TURN **ON** OR **OFF** THE **AREA** YOU HAVE SELECTED.
- THE ALARM SYSTEM WILL TEST ALL OF THE SENSORS IN THE **AREA** YOU HAVE REQUESTED TO TURN **ON** BEFORE THE SYSTEM WILL ALLOW THAT **AREA** TO TURN **ON**. ANY UNSEALED SENSORS WILL PREVENT THE **AREA** FROM TURNING **ON**.
- CHECK ALL OF THE UNSEALED SENSORS AND RETRY TO TURN THE **AREA ON**. IF YOU ARE UNABLE TO SEAL ANY OF THE UNSEALED SENSORS THEY CAN BE ISOLATED DURING THE ARMING SEQUENCE BY PRESSING THE **FORCE** KEY WHEN PROMPTED.

INSTALLED AND
SERVICED BY
VISION SYSTEMS
PHONE (03) 3773424



VISION SYSTEMS
PROFESSIONAL SECURITY SOLUTIONS